

Printing

Printing from laptops

There is a [separate page about the printer setup on personal laptops](#).

Queuing your print



The command `'printers'` should give you a list of printers available to people at the observatory, and the location of them. After selecting the closest one to you (or one a little further in case you missed your workout) you can print (postscript!) files with the command `'lpr -P[your printer] myfile.ps'`

Alternatively you can print *any!* file with `print myfile.anyextension`. Print is a program that determines the type of file to be printed and then selects the appropriate program that can make postscript from the to-be-printed file.

When you think you wouldn't mind using your selected printer for a longer period you can set it as default with the command `'setenv PRINTER [your printer]'`. This line, when inserted in the `.settings` file in your homedirectory, will allow you to print any postscript file with just `'print myfile.ps'`.

Tracking your printjob

To find out what the print status of your print job is you can type the command: `lpq` or `lpq -P[your printer]`. The ordering of the jobs is top is actively being printed, down in the list will be printer later.

If you by accident queued a wrong file in the printer queue you may remove your entries by having noted the job ID number and running the command: `lprm [ID number]`, or `lprm -P[your printer] [ID number]`.

Here are some more commands as examples:

Command	Description
<code>lpstat -p</code>	Display a list and state of available printers
<code>lpr -Pprinter-name doc.pdf</code>	Print <i>doc.pdf</i> on <i>printer-name</i>
<code>lpq -Pprinter-name</code>	Show the current print queue on the named printer

Command	Description
<code>lprm -Pprinter-name job-id</code>	Remove a job from the queue, the <i>job-id</i> can be found in the <i>lpq</i> output
<code>lpstat -v</code>	Display Printers connecton info
<code>printers</code>	Display printer information from our database

Printer errors

Recently, we are experiencing lots of printer errors. These are usually caused by strange postscript or pdf files that fail to print. If you see a printer displaying such an error, first check if your print job is the first in the queue. if it is, it's probably your job that caused the error somehow, so DON'T sent the same job to all the other printers to see if it print there.

Often, these jobs are truncated due to lack of disk space, either in your user home disk quota, or in the /var partition of your computer where the job is spooled before printing. Check and solve these problems first, and chances are that the printing problem will be solved also.

~~Acrobat reader can cause such an error if "download Asian fonts" is checked in the print dialog, since we don't have those fonts, it will cause an incomplete print job to be sent to the printer.~~

Doublesided printers

For environmental, and financial, reasons you are encouraged (read urged) to use the double-sided printers for your normal printing jobs. On most printers and copiers, this will be the default already.

When printing drafts you can also use the program 'psnup' to output two pages on one sheet to save even more paper. A working example is: `'cat somefile.ps | psnup -2 | lpr -P[your printer]'` (2 pages on one) or (When you don't need glasses) `'cat somefile.ps | psnup -4 | lpr -P[your printer]'` (4 pages on one)

The environment will thank you!

STRW printers

Name	Location	Type
BW3copier	GOB 3rd floor, BW wing	Canon copier iR-ADV C5860/5870 (download driver)
BW4copier	GOB 4rd floor, BW wing	Canon copier iR-ADV C5860/5870 (download driver)
HL5printer	Corridor Huygens 5th floor Color	HP Color LaserJet 4600
marijn_desk	Personal printer for Marijn Franx	HP LaserJet 6MP
novaoffice	BW246, NOVA office	HP Color LaserJet cp2025n
schaye_desk	Personal printer for Joop Schaye	HP Color LaserJet 2605dn
secr1	GOB BM 4.12	HP Color LaserJet 3000
secr3	GOB BW 4.01	HP Color LaserJet cp2025dn (Chatelaine/Ignas)
sysadmins	HL Room 406	HP LaserJet 400 color M452dn

Lorentz Institute Printers

Name	Location	Type	Model
lorentz_small	Corridor Oort 2nd floor	Color	HP Color LaserJet cp4520
lorentz_medium	Corridor Oort 2nd floor	Color	HP Color LaserJet M553
oort2copier	Corridor Oort 2nd floor	Color	Canon copier iR-ADV C5860/5870 (download driver)
oort1-color	Corridor Oort 1st floor	Color	HP Color LaserJet cp2025

Multifunctional Copiers/Printers

These systems are not managed by the support team of the institute, although we handle the print queues and can solve minor problems with these devices.

If you experience any problems with them such as jams, out of toner or more complex errors, please do not hesitate to contact helpdesk-multifunctionals@UFB.leidenuniv.nl citing the location of the printer and its name/code which you will find on the printer itself.

From:

<https://helpdesk.physics.leidenuniv.nl/wiki/> - **Computer Documentation Wiki**

Permanent link:

<https://helpdesk.physics.leidenuniv.nl/wiki/doku.php?id=printing&rev=1712303385>

Last update: **2024/04/05 07:49**

